

# INT69 F Diagnose

## Parameter table 22 A 712 P081



Parameters can be read with function code 3 (Read Holding Register) and written with function code 6 (Write single register).

### INT69 F Diagnose

Parameter	Range	Default	Unit
<b>Engine temperature</b>			
Sensor type	Disabled, Pt100, Pt1000, PTC, Bimetal	PTC	
Designation	0...40 character	Designation	
Motor temperature trip point temperature	-100...300	140	°C
Warning temperature	-100...300	110	°C
Hysteresis	0...300	30	K
Trip delay	00:00.1...59:59.9	00:00.1	mm:ss.f
Reset delay	00:00:00...18:12:14, locked	locked	hh:mm:ss
Line correction	0.0...100.0	0.0	⊘
<b>Temperature 1</b>			
Sensor type	Disabled, Pt100, Pt1000, PTC, Bimetal	Disabled	
Designation	0...40 character	Designation	
Trip point temperature	-100...300	150	°C
Warning point temperature	-100...300	130	°C
hysteresis	0...300	30	K
Trip delay	00:00.1...59:59.9	00:00.1	mm:ss.f
Reset delay	00:00:00...18:12:14, locked	00:00:00	hh:mm:ss
Line correction	0.0...100.0	0.0	⊘
<b>Leakage 1</b>			
Operating mode	Disabled, Exceed resistance, Resistance below	Resistance below	
Designation	0...40 character	Designation	
Trip point value	5...1500	60	k⊘
Warning value	5...1500	75	k⊘
hysteresis	1...999	10	k⊘
Trip delay	00:00.1...59:59.9	01:00.0	mm:ss.f

## INT69 F Diagnose

Parameter	Range	Default	Unit
Reset delay	00:00:00...18:12:14, locked	00:00:00	hh:mm:ss

### Service interval

Status	Disabled, restart, Active	Disabled	
Service interval duration	100...26280	24000	h

### Relay 1

Selection of alarms 1	Bit 00: Engine temperature	Engine temperature
	Bit 01: Temperature 1	Temperature 1
	Bit 02: Leakage 1	-
	Bit 03: self-monitoring	self-monitoring
Select warnings	Bit 00: Engine temperature	-
	Bit 01: Temperature 1	-
	Bit 02: Leakage 1	-
	Bit 03: Service interval	-

### Relay 2

Selection of alarms 1	Bit 00: Engine temperature	-
	Bit 01: Temperature 1	-
	Bit 02: Leakage 1	Leakage 1
	Bit 03: self-monitoring	self-monitoring
Select warnings	Bit 00: Engine temperature	-
	Bit 01: Temperature 1	-
	Bit 02: Leakage 1	-
	Bit 03: Service interval	-

## KRIWAN Industrie-Elektronik GmbH

Allmand 11  
74653 Forchtenberg  
Germany

Phone (+49) 7940 822 0

info@kriwan.de  
www.kriwan.com